

## SAFETY INSTRUCTIONS

Please follow the instructions for use of the Erica Synths module below, 'cause only this will guarantee proper operation of the module and ensure warranty from Erica Synths.



Water is lethal for most of the electric devices, unless they are made waterproof. This Erica Synths module is NOT intended for use in a humid or wet environment. No liquids or other conducting substances must get into the module. Should this happen, the module should be disconnected from mains power immediately, dried, examined and cleaned by a qualified technician.



Do not expose the module to temperatures above +50° C or below -20° C. If you have transported module in extreme low temperatures, leave it in room temperature for an hour before plugging it in.



Transport the instrument carefully, never let it drop or fall over. Warranty does not apply to modules with visual damages.



The module has to be shipped in the original packaging only. Any module shipped to us for return, exchange and/or warranty repair has to be in its original packaging. All other deliveries will be rejected and returned to you. Make sure you keep the original packaging and technical documentation.



This device complies to the EU guidelines and is manufactured RoHS conforming without use of lead, mercury, cadmium and chrome. Nevertheless, this device is special waste and disposal in household waste is not recommended.

You will find Erica Synths terms of warranty at [www.ericasynths.lv](http://www.ericasynths.lv)

Items for return, exchange and/or warranty repair have to be sent to:

Erica Synths  
Andrejostas Str. 43  
Riga  
Latvia  
LV-1045

User manual by Girts Ozolins@Erica Synths.

Design by Ineta Briede@Carre Branding.

Copying, distribution or any commercial use in any way is prohibited and needs the written permission by Erica Synths.

Specifications are subject to change without notice.

In case of any questions, feel free to contact us through [www.ericasynths.lv](http://www.ericasynths.lv) or via e-mail [info@ericasynths.lv](mailto:info@ericasynths.lv)

## THANK YOU FOR PURCHASING ERICA SYNTHS DRUM MODULE!

Erica Drum Series modules include high-end, unique functionality and superior quality modules, which allow you to design extensive, feature rich modular system for sound design and live performances.

Erica Synths TOMS module is developed in collaboration with the French company e-licktronic and it's our take on analogue toms circuits adapted for modular systems. Massive, punchy sound, Accent and Tone CV make it distinctively expressive in studio and live performances.

## FEATURES

Low, Mid and High Tom in one module  
Pitch and Decay controls  
Pitch CV control with attenuator  
Manual trigger  
Accent for better expression

## SPECS

Decay range	370ms - 955ms
Audio output level	-5...+5V
CV level (full span)	-5V - +5V
Accent CV level	10V
Trigger level	5V
Trigger time	1ms
Power consumption	83mA @ +12V, 76mA @ -12V
Module width	16HP
Module depth	50mm

# TOMS



### PITCH

Set the initial pitch of each Tom manually!

### DECAY

Adjust decay time of each Tom

### PITCH CV

These are pitch CV attenuators

### TRIG

Use the manual trigger buttons to check the toms settings and add some triggers during live performance

### TRIG IN

These are the Trigger inputs. The LEDs indicate incoming triggers

### ACC

These are the Accent inputs. +10V CV will set the tom to the maximum volume.

### OUT

These are the outputs of each tom



# TOMS

